

HD-SDI/HDMI Converter

Art.-Nr. TVAC22001



- Conversion of an HD-SDI signal to an HDMI interface
- HD-SDI standard SMPTE 292M
- Scaling of the video signal for different monitor resolutions
- Control function for a monitor matrix (TV wall function)
- Plug & play installation
- Dual mode: HDMI (1 ×) and HD-SDI (2 ×)
- Suited as a dual distributor for HD-SDI signals

This converter converts an HD-SDI camera signal into an HDMI interface.

This enables you to directly connect an HD-SDI camera to a monitor with an HDMI input. The converter can be adjusted to the resolution of the available monitor (1080p25 mode is not required).

In addition, the converter has two actively amplified HD-SDI outputs (BNC). This means the HD-SDI signal can be distributed and forwarded, for example, to an HD-SDI digital recorder as well as to an HD-SDI monitor or another HDMI converter.

Technical Data

Certifications	CE
Connections	2x BNC (HD-SDI), 1x HDMI (Typ A)
DC voltage supply	6 – 15V
Height	26mm
Input	1x BNC (HD-SDI)
Length	104mm

Max. operating temperature	50°C
Min. operating temperature	0°C
Output	1x BNC (HD-SDI), 1x HDMI (Typ A)
Power consumption	500mA
Width	64mm