

Smartvest Wireless Remote Control

Art.-Nr. FUBE35001A



-
- Smartvest extension for operation without a mobile device
 - Immediate operation at the push of a button and with no need for a PIN code
 - Buttons for arming and disarming the Smartvest
 - Panic alarm that can be triggered at the push of a button
 - Individual configuration of buttons to automatically activate additional components (cameras, sirens, etc.) simultaneously
 - Visual feedback via blue LED
 - Low battery notification sent to the Smartvest alarm control panel
 - Small, portable and easy to use
 - Security-mechanism for protection against Replay-attacks
-

In addition to the smartphone and tablet option, the Smartvest Wireless Remote Control offers you another streamlined and convenient option for operation – at the push of a button, without the need for a PIN code. With this option, you can both arm and disarm the Smartvest or, in an emergency, trigger a panic alarm at the touch of a button. Using the app, the button can also be configured so that certain cameras or the siren are activated when the buttons are pressed. The Smartvest Wireless Remote Control thus provides basic control options in a compact and handy form ensuring it is simple and intuitive to use.

Remark:

The Smartvest Wireless Remote Control is protected against so-called replay attacks by an integrated security mechanism. All switching commands to the Smartvest alarm panel are individualized and thus not reproducible by unauthorized third parties.

Smartvest Wireless Remote Control

Art.-Nr. FUBE35001A

Technical Data

Battery operation	Yes
Battery quantity	1
Battery type	CR2032 (3V)
Color	White
Compatible with Secvest	No
Compatible with Smartvest	Yes
Display	LED
Gross weight	0,056kg
Housing material	Plastic
Max. battery life	2year(s)
Max. humidity	80%
Max. operating temperature	40°C

Min. humidity	10
Min. operating temperature	0°C
Net weight	0,022kg
Power consumption	15mA
Power consumption Standby	0,005mA
Radio frequency	868MHz
Transmission power	4,5 dBm
Wireless modulation	FSK
Wireless range	(Depending on installation) 30 - 100m