

## **Smartvest Wireless Motion Detector**

Art.-Nr. FUBW35000A



- Smartvest extension for monitoring rooms
- Quick and cable-free installation without the need for wires or drilling thanks to battery operation
- Detection of people using infrared with a horizontal detection range of 105° and a maximum range of 12 m
- Visual notification via blue LED when starting up and functioning
- Automatic supervision, with functional tests repeated daily and feedback sent to the Smartvest alarm control panel
- Low battery notification sent to the Smartvest alarm control panel
- Battery life of up to 2 years
- Tamper protection via cover contact

The Smartvest Wireless Motion Detector enables you to monitor rooms, while its battery operation makes it easy to install, avoiding the need for drilling and wiring. It can be relied upon to detect people in the room using infrared, and has a range of up to 12 metres. When the battery is low, the Smartvest Wireless Motion Detector sends an automatic notification to the alarm panel. The free Smartvest app then guides you step by step through the process of replacing the batteries. In combination with the Smartvest Wireless Socket, you can then initiate certain smart functions such as "motion detected" or "light on", in addition to monitoring.



## **Smartvest Wireless Motion Detector**

## Art.-Nr. FUBW35000A

## **Technical Data**

Areas of usage	Inside
Battery operation	Yes
Battery quantity	3
Battery type	AA (1,5V)
Color	White
Compatible with Secvest	No
Compatible with Smartvest	Yes
Display	LED
Gross weight	0,252kg
Housing material	Plastic
Max. battery life	2year(s)
Max. humidity	80%
Max. operating	40°C
temperature	
Min. humidity	10
Min. operating	0°C
temperature	

Not weight	0.544
Net weight	0,54kg
PIR angle of view	Horizontal: 105° / Vertical:
	45°
Pet-proof	No
Power consumption	15mA
Power consumption	0,03mA
Standby	
Radio frequency	868MHz
Sensor type	PIR
Tamper protection	No
Transmission power	4,5 dBm
Type of detection	Heat detection
Wireless modulation	FSK
Wireless range	(Depending on installation)
	30 - 100m
Wireless modulation	FSK (Depending on installation