

## Smartvest Wireless Socket

Art.-Nr. FUHA35000A

---



- 
- Smartvest extension for switching connected devices
  - Smart light control: system armed/disarmed, motion detected, light on
  - Visual notification via blue LED when starting up and functioning
  - Repeater function to extend the range of a Smartvest component (e.g. detector)
  - Manual switching on socket possible
  - Option to control the socket via the Smartvest app
- 

The Smartvest Wireless Socket enables you to switch on a number of your electronic devices, with the option to do this either yourself via the free and convenient app or automatically via a personalised time schedule. In other words, it gives you the option of different smart functions, such as presence simulation or setting the coffee machine to switch on before you have got out of bed. There are almost no limits on what you can do with the Socket and app, which gives everyday life the level of "smartness" and security it should have.

## Smartvest Wireless Socket

Art.-Nr. FUHA35000A

### Technical Data

AC voltage supply	250V
Areas of usage	Inside
Certifications	GS
Color	White
Compatible with Secvest	No
Compatible with Smartvest	Yes
Connector type	Schuko plug on device (type:F) / Schuko socket on device (type:F)
Display	LED
Gross weight	0,176kg
Housing material	Plastic
Luminous color	Blue / Orange
Max. humidity	80%

Max. operating temperature	35°C
Min. operating temperature	0°C
Net weight	0,129kg
Power consumption Standby	10mA
Radio frequency	868MHz
Switching power	< 3680W
Tamper protection	No
Transmission power	4,5 dBm
Wireless modulation	FSK
Wireless range	(Depending on installation) 30 - 100m